



# DAR SERIES

## Flagship 4ch Digital Karaoke Amplifier with Higher Efficiency of Power Conversion

- The amplifier uses exclusive device to get 95% or higher efficiency of power conversion to reduce heat generation.
- Improved consolidation ratio reduced the number of parts. Consequently, noise and the influence of background noise have been cut down dramatically.
- The use of BTL connection enables the amplifier to be used as a high power amplifier (BTL Power: 360Wx2ch).



### DAR-800 II (SE)

- Max Output Power: 150W × 4CH (8Ω, EIAJ) : 4 speakers system  
360W × 2CH (8Ω, EIAJ) : 2 speakers system
- Main Pitch Degree: 13degrees ± 3.0DSP
- Audio Input: 5 systems (KARAOKE, DVD, AUX, BGM, TAPE)
- Video Input: 3 systems (KARAOKE, DVD, CAMERA)
- Mic Input: 5 systems : front 3, rear 2
- Sound Change: ON / OFF (TACT-SW)
- Sound Effects: 11 modes
- Feedback Reduce: ON / OFF (TACT-SW)
- AC Input: 230V ~ 240V
- Dimensions (mm): 420(W) × 142(H) × 396(D)
- Weight: 17.1kg

